

**ORIGINATION FORM**  
**Proposed Revisions to the Specifications**  
(Please provide all information - incomplete forms will be returned)

**Date:** \_\_\_\_\_ **Office:** \_\_\_\_\_  
**Originator:** \_\_\_\_\_ **Specification Section:** \_\_\_\_\_  
**Telephone:** \_\_\_\_\_ **Article/Subarticle:** \_\_\_\_\_  
**email:** \_\_\_\_\_ **Associated Section(s) Revisions:** \_\_\_\_\_

**Will the proposed revision require changes to the following Publications:**

<b>Publication</b>	<b>Yes</b>	<b>No</b>	<b>Office Staff Contacted</b>	<b>Date</b>
Standard Plans Index				
Traffic Engineering Manual				
FDOT Design Manual				
Construction Project Administration Manual				
Basis of Estimate/Pay Items				
Structures Design Guidelines				
Approved Product List				
Materials Manual				
Maintenance Specs				

**Will this revision necessitate any of the following:**

**Design Bulletin      Construction (DCE Memo)      Estimates Bulletin      Materials Bulletin**

**Have all references to internal and external publications in this Section been verified for accuracy?**

**Synopsis: Summarize the changes:**

**Justification: Why does the existing language need to be changed?**

**Do the changes affect either of the following types of specifications (Hover over type to go to site.):**

**[Special Provisions](#)      [Developmental Specifications](#)**

**List Specifications Affected: (ex. SP3270301, Dev330TL, Dev334TL etc.)**

**Contact the State Specifications Office for assistance completing this form.**

1. Are changes in line with promoting and making meaningful progress on improving safety, enhancing mobility, inspiring innovation, and fostering talent; explain how?
2. What financial impact does the change have; project costs, pay item structure, or consultant fees?
3. What impacts does the change have on production or construction schedules?
4. How does this change improve efficiency or quality?
5. Which FDOT offices does the change impact?
6. What is the impact to districts with this change?
7. Does the change shift risk and to who?
8. Provide summary and resolution of any outstanding comments from the districts or industry.
9. What is the communication plan?
10. What is the schedule for implementation?

Please note this revision has several instances of moved language.

## NETWORK DEVICES.

(REV 9-28-23)

SECTION 684 is deleted and the following substituted:

### SECTION 684 NETWORK DEVICES

#### ~~684-1 Managed Field Ethernet Switch.~~

##### ~~684-1.1 Description:~~

~~Furnish and install a hardened, device level managed field Ethernet switch (MFES) for intelligent transportation system (ITS) projects. Ensure that the MFES provides wire speed fast Ethernet connectivity at transmission rates of 100 megabits per second from the remote ITS device installation location to the ITS network trunk interconnection point.~~

~~684-1.2 Materials: All equipment shall be permanently marked with manufacturer name or trademark, part number, and date of manufacture or serial number devices as shown in the Plans. Meet the requirements of Section 603. Use only equipment and components that meet the~~

#### ~~684-2 Materials.~~

~~684-2.1 General: Meet the following requirements of:~~

<del>Managed Field Ethernet Switch*</del> .....	<del>Section 996 and are</del>
<del>Managed Hub Ethernet Switch</del> .....	<del>Section 996</del>
<del>Device Server*</del> .....	<del>Section 996</del>
<del>Digital Video Encoder*</del> .....	<del>Section 996</del>
<del>Digital Video Decoder*</del> .....	<del>Section 996</del>
<del>Media Converter*</del> .....	<del>Section 996</del>

~~\*Use products listed on the Department's Approved Product List (APL).~~

~~684-2.2 Managed Field Ethernet Switch: Ensure that the managed field Ethernet switch (MFES) provides Ethernet connectivity between devices, systems, and locations as required by the Contract Documents.~~

Ensure that the ITS network administrator will be able to manage each MFES individually and as a group for switch configuration, performance monitoring, and troubleshooting.

Ensure that the ~~furnished~~ MFES is fully compatible and interoperable with field devices and the ~~ITS trunk Ethernet traffic control system~~ network ~~interface~~.

~~Provide~~ Ensure the MFES provides a switched Ethernet connection for each ~~remote ITS field connected~~ device and at least one open RJ45 Ethernet port for technician access.

~~684-12.2.1 Optical Ports:~~ Ensure that all fiber optic link ports operate at 1,310 or 1,550 nanometers in single mode. Ensure that the optical ports are Type ST, SC, LC, or FC only, as specified in the Plans or by the Engineer. Do not use mechanical transfer registered jack (MTRJ) type connectors.

Provide an MFES having a minimum of two optical 100 Base FX ports capable of transmitting data at 100 megabits per second unless otherwise shown in the Plans. Ensure the MFES is configured with the number and type of ports detailed in the Contract Documents. Provide optical ports designed for use with a pair of fibers; one fiber will transmit

Please note this revision has several instances of moved language.

(TX) data and one fiber will receive (RX) data. The optical ports must have an optical power budget of at least 15 dB, or as detailed in the Contract Documents.

~~684-1.2.2~~ **Copper Ports:** Provide an MFES that includes a minimum of four copper ports unless otherwise shown in the Plans.

Ethernet over very high speed digital subscriber line (EoVDSL) ports are permitted for use in applications where fiber optic cable is not available.

~~684-1.3~~ **Installation:** Mount the MFES inside a field site cabinet. Ensure that the MFES is resistant to all electromagnetic interference (EMI). Ensure that the MFES is mounted securely and is fully accessible by field technicians. Ensure that all unshielded twisted pair/shielded twisted pair Ethernet network cables are compliant with the EIA/TIA-568-B standard.

~~684-1.4~~ **Field Acceptance Testing:** Conduct field acceptance testing in accordance Section 611.

~~Once the MFES has been installed, conduct local field inspection at the MFES field site according to the approved test plan. Perform the following:~~

~~684-2.3~~ **Managed Hub Ethernet Switch:** Ensure that the managed hub Ethernet switch (MHES) provides wire-speed fast Ethernet connectivity at transmission rates of both one and ten gigabits per second to and from adjacent MHES within the traffic control network.

~~Ensure that the ITS network administrator will be able to manage each MHES individually and as a group for switch configuration, performance monitoring, and troubleshooting.~~

~~Ensure that the MHES is fully compatible and interoperable with field devices and the traffic control system network.~~

~~Ensure the MHES includes any license(s) required to utilize all Layer 3 features.~~

~~Ensure the MHES provides~~ 1. Verify that physical construction has been completed as detailed in the Plans.

~~connections.~~ 2. Inspect the quality and tightness of ground and surge protector

~~connections.~~ 3. Verify proper voltages for all power supplies and related power circuits.

~~connections.~~ 4. Connect devices to the power sources.

~~connections.~~ 5. Verify all connections, including correct installation of communication and power cables.

~~684-2~~ Device Server.

~~684-2.1~~ **Description:** ~~Furnish and install~~ a switched Ethernet connection for each connected device server as and at least one open RJ45 Ethernet port for technician access.

~~684-2.3.1~~ **Optical Ports:** Ensure that all fiber optic link ports are modular SFP/SFP+ ports that operate at 1310 or 1550 nanometers in single mode. Ensure that the optical ports are Type LC unless otherwise shown in the Plans. Do not use mechanical transfer registered jack (MTRJ) type connectors.

~~684-2.2~~ **Materials:** All equipment must be permanently marked with manufacturer name or trademark, part number, and date of manufacture or serial number. Meet the requirements of Section 603. Use only equipment and components that meet the requirements of Section 996 and are listed on the APL.

~~Verify that all wiring meets applicable NEC requirements and that the device server operates~~

Provide an MHES having a minimum of six optical Gigabit Ethernet ports capable of transmitting data at one gigabit per second and 10 gigabits per second unless otherwise shown in the Plans. Ensure the MHES is configured with the number and type

Please note this revision has several instances of moved language.

of ports detailed in the Contract Documents. Furnish all hot-swappable Gigabit Interface Converter (GBIC) fiber optical transceivers. Provide optical ports designed for use with a pair of fibers; one fiber will transmit (TX) data and one fiber will receive (RX) data. The optical ports must have an optical power budget of at least 15 dB, or as detailed in the Contract Documents.

**684-2.3.2 Copper Ports:** Provide an MHES that includes a minimum of twelve gigabit Ethernet end user copper ports unless otherwise shown in the Plans. All copper ports must be Type RJ-45 and auto-negotiate speed (i.e., 10/100/1000 Base) and duplex (i.e., full or half).

**684-2.4 Device Server:** Ensure that the device server provides Ethernet connectivity to devices with serial data interfaces as required by the Contract Documents. The device server must operate using a nominal input voltage of 120 V<sub>AC</sub>. If the device requires nominal input voltage of less than 120 V<sub>AC</sub>, furnish the appropriate voltage converter.

~~**684-2.3 Installation:** Mount the device server securely in a location in the equipment cabinet that allows the unit to be fully accessible by field technicians. Ensure that all unshielded twisted pair/shielded twisted pair Ethernet network cables are compliant with the EIA/TIA 568-B standard.~~

~~**684-2.4 Field Acceptance Testing:**~~

~~Develop and submit a field acceptance test FAT plan to the Engineer for review and approval. The Engineer reserves the right to witness all FATs.~~

~~Perform local field operational tests at device server field sites according to the test procedures stated herein.~~

~~1. Verify that physical construction has been completed as specified in the Plans.~~

~~2. Verify the quality and tightness of ground and surge protector connections.~~

~~3. Verify proper voltages for all power supplies and related power circuits.~~

~~4. Connect devices to the power sources.~~

~~5. Verify all connections, including correct installation of communication and power cables.~~

~~6. Verify the network connection to the device server through ping and telnet session from a remote PC.~~

~~7. Verify serial data transmission through the device server.~~

### **684-3 Digital Video Encoder and Decoder:**

~~**684-3.1 Description:** Furnish and install digital video encoder (DVE) and digital video decoder (DVD) hardware and software to create a video over IP network system, as shown in the Plans.~~

~~**684-3.2 Materials:** All equipment shall be permanently marked with manufacturer name or trademark, part number, and date of manufacture or serial number. Meet the requirements of Section 603. Use only equipment and components that meet the requirements of Section 996, and are listed on the APL.~~

~~**:** Ensure that the complete video and data transmission system, defined as the combination of digital video encoder (DVE) and digital video decoder (DVD) hardware together with the existing or planned network infrastructure, simultaneously transports video and data from multiple remote field locations to multiple monitoring locations for roadway surveillance and traffic management.~~

Please note this revision has several instances of moved language.

Provide a software decoding and control package that allows the viewing of any video source connected to the network through a DVE, and which allows the pan-tilt-zoom (PTZ) control of any PTZ camera on the network, the discovery of DVE and DVD devices on the network, and the control and adjustment of programmable parameters in the DVE and DVD equipment, including the network addresses of these devices, at no additional cost.

**684-3.2.5.1 Digital Video Decoder:** Provide a DVD that is either a hardware-based network device or a software application that resides on a workstation PC. Ensure that the software application provides PC desktop display of IP network video streams.

Provide all setup, control programs, and diagnostic software related to the DVE or DVD.

Provide all equipment licenses, where required for any software or hardware in the system.

Ensure that any software-based decoder applications do not interfere with SunGuide® software operating when installed and used together on a shared hardware platform. Ensure that the software-based decoder offers an open Application Programming Interface (API) and software development kit available to the Department at no cost for integration with third party software and systems.

**684-3.2.5.2 Interoperability:** Provide DVE and DVD devices and software that are interoperable and interchangeable with DVE and DVD devices and software from other manufacturers.

**684-3.2.5.3 Network Interface:** Ensure that fiber ports are single mode with a minimum link budget of 30 dB or the type and power detailed in the Contract Documents.

~~684-3.3 Installation: Ensure that front panel status indicators remain unobstructed and visible. Ensure that all unshielded twisted pair/shielded twisted pair network cables are compliant with the EIA/TIA 568-B standard.~~

~~684-3.4 Field Acceptance Testing: Develop and submit a field acceptance test FAT plan to the Engineer for review and approval. The Engineer reserves the right to witness all FATs.~~

~~Perform local field operational tests at the device field site and end-to-end video streaming tests in order to demonstrate compliance with Department specifications. Testing will include, but not be limited to, the following:~~

~~**684-2.6 Media Converter:** 1. Verify that physical construction has been completed as detailed in the Plans.~~

~~2. Inspect the quality and tightness of ground and surge protector connections.~~

~~3. Verify proper voltages for all power supplies and related power circuits.~~

~~4. Connect devices to the power sources.~~

~~5. Verify all connections, including correct installation of communication and power cables.~~

~~6. Verify video image is present and free from oversaturation and any other image defect in both color and monochrome mode.~~

~~7. Verify network connection to the DVE and DVD through ping and telnet session from a remote PC.~~

~~8. Verify serial data transmission through the DVE and DVD serial ports.~~

~~9. Verify support of unicast, multicast, and SAP.~~

~~684-4 Media Converter:~~

~~684-4.1 Description: Furnish and install a media converter as shown in the Plans.~~

Please note this revision has several instances of moved language.

~~684-4.2 Materials: All equipment shall be permanently marked with manufacturer name or trademark, part number, and date of manufacture or serial number. Meet the requirements of Section 603. Use only equipment and components that meet the requirements of Section 996 and are listed on the APL.~~

~~The media converter must allow transition between the transmission media shown in the Plans or required to construct a functional system, such as conversion from twisted pair to optical fiber or from twisted pair to coaxial cable.~~

~~Ensure that fiber ports are single mode with a minimum link budget of 30 dB or the type and power detailed in the Contract Documents.~~

~~Media converters must operate on a nominal voltage of 120 V<sub>AC</sub> if POE is unavailable. Supply an appropriate voltage converter for devices that require operating voltages of less than 120 V<sub>AC</sub>.~~

~~684-4.3 Installation: Ensure that status indicators remain unobstructed and visible. All parts must be made of corrosion resistant materials, such as plastic, stainless steel, anodized or painted aluminum, brass, or gold plated metal. Ensure that all unshielded twisted pair/shielded twisted pair Ethernet network cables are compliant with the EIA/TIA-568-B standard.~~

### **684-3 Installation.**

**684-3.1 General:** Install network devices at the locations shown in the Plans. Ensure that network devices are mounted securely and is fully accessible by field technicians. Ensure that all unshielded twisted pair/shielded twisted pair Ethernet network cables are compliant with the EIA/TIA-568-B standard.

### **684-4 Field Acceptance Testing.**

**684-4.1 General:** Conduct field acceptance testing in accordance Section 611.

**684-4.2 MFES Field Acceptance Testing:** Conduct inspection and testing at the installed equipment location according to the approved test plan. Perform the following:

1. Verify that physical construction has been completed as detailed in the Plans.
2. Inspect the quality and tightness of ground and surge protector connections.
3. Verify proper voltages for all power supplies and related power circuits.
4. Connect devices to the power sources.
5. Verify all connections, including correct installation of communication and power cables.

6. Verify network connection and MFES configuration using a laptop PC.

**684-4.3 MHES Field Acceptance Testing:** Conduct inspection and testing at the installed equipment location according to the approved test plan. Perform the following:

1. Verify that physical construction has been completed as detailed in the Plans.
2. Inspect the quality and tightness of ground and surge protector connections.
3. Verify proper voltages for all power supplies and related power circuits.
4. Connect devices to the power sources.
5. Verify all connections, including correct installation of communication and power cables.

6. Verify network connection and MHES configuration using a laptop PC.

**684-4.4 Device Server Field Acceptance Testing:** Conduct inspection and testing at the installed equipment location according to the approved test plan. Perform the following:

1. Verify that physical construction has been completed as specified in the Plans.
2. Verify the quality and tightness of ground and surge protector connections.



Please note this revision has several instances of moved language.

- \_\_\_\_\_ 3. Verify proper voltages for all power supplies and related power circuits.
- \_\_\_\_\_ 4. Connect devices to the power sources.
- \_\_\_\_\_ 5. Verify all connections, including correct installation of communication and power cables.
- \_\_\_\_\_ 6. Verify network connection and device server configuration using a laptop PC.
- \_\_\_\_\_ 7. Verify serial data transmission through the device server.

**684-4.5 DVE and DVD Field Acceptance Testing: Conduct inspection and testing at the installed equipment location according to the approved test plan. Perform the following:**

- \_\_\_\_\_ 1. Verify that physical construction has been completed as detailed in the Plans.
- \_\_\_\_\_ 2. Inspect the quality and tightness of ground and surge protector connections.
- \_\_\_\_\_ 3. Verify proper voltages for all power supplies and related power circuits.
- \_\_\_\_\_ 4. Connect devices to the power sources.
- \_\_\_\_\_ 5. Verify all connections, including correct installation of communication and power cables.
- \_\_\_\_\_ 6. Verify video image is present and free from oversaturation and any other image defect in both color and monochrome mode.
- \_\_\_\_\_ 7. Verify network connection to the DVE and DVD through ping and telnet session from a remote PC.
- \_\_\_\_\_ 8. Verify serial data transmission through the DVE and DVD serial ports.
- \_\_\_\_\_ 9. Verify support of unicast, multicast, and SAP.

#### **684-5 Warranty.**

**684-5.1 General:** Ensure that network devices have a manufacturer's warranty covering defects for 1 year from the date of final acceptance. Ensure that the manufacturer will furnish replacements for any part or equipment found to be defective during the warranty period at no cost to the Department or the maintaining agency within 10 calendar days of notification.

~~\_\_\_\_\_ **684-5.2 MFES:** Ensure that the MFES has a manufacturer's warranty covering defects for five years from the date of final acceptance by the Engineer in accordance with 5-11 and Section 608.~~

~~\_\_\_\_\_ **684-5.3 Device Server:** Ensure that the device server has a manufacturer's warranty covering defects for five years from the date of final acceptance by the Engineer in accordance with 5-11 and Section 608.~~

~~\_\_\_\_\_ **684-5.4 Digital Video Encoder and Decoder:** Ensure that the DVE or DVD has a manufacturer's warranty covering defects for two years from the date of final acceptance by the Engineer in accordance with 5-11 and Section 608.~~

~~\_\_\_\_\_ **684-5.5 Media Converter:** Ensure that the media converter has a manufacturer's warranty covering defects for five years from the date of final acceptance by the Engineer in accordance with 5-11 and Section 608.~~

#### **684-6 Method of Measurement.**

The Contract unit price for each MFES, network device ~~server, DVE, DVD, or media converter,~~ furnished and installed, will include furnishing, placement, and testing of all equipment and materials, and for all tools, labor, hardware, operational software packages and firmware, supplies, support, personnel training, shop drawings, documentation, and incidentals necessary to complete the work.

Provide software-based decoders at no additional cost when furnished in conjunction with DVEs.



Please note this revision has several instances of moved language.

| \_\_\_\_\_ A software-based DVD provided individually must be paid under the pay item below.

**684-7 Basis of Payment.**

Price and payment will be full compensation for all work specified in this Section.

Payment will be made under:

- Item No. 684- 1- Managed Field Ethernet Switch-each.
- Item No. 684- 2- Device Server-each.
- Item No. 684- 3- Digital Video Encoder with Software Decoder-each.
- Item No. 684- 4- Digital Video Decoder-each.
- Item No. 684- 5- Media Converter-each.
- Item No. 684- 7- Managed Hub Ethernet Switch--each