

# EXPECTED IMPLEMENTATION JULY 2022

## MAINTENANCE OF TRAFFIC

(REV 11-23-21) (FA 2-22-22) (7-22)

SUBARTICLE 102-9.11 is deleted and the following substituted:

**102-9.11 Portable Changeable Message Sign (PCMS):** Furnish PCMSs or truck mounted changeable message signs that meet the requirements of Section 990 as required by the Plans and Standard Plans to supplement other temporary traffic control devices used in work zones. Ensure that the PCMS display panel is raised to a fully upright position and is visible to motorists from 1/2 mile, or a distance approved by the Engineer, under both day and night conditions. Use PCMS with a minimum letter height of 18 inches. For facilities with posted speed limits of 45 mph or less, PCMS with a minimum letter height of 12 inches may be used.

For roadways with speed limits greater than 45 mph, the message displayed on the PCMS must be unobstructed from 800 feet. For roadways with speed limits of 45 mph or less, the message displayed must be unobstructed from 650 feet.

Messages must have no more than two phases. The display time for each phase must be at least two seconds but no more than three seconds. The sum of the display time must be a maximum of six seconds.

SUBARTICLE 102-9.15 is deleted and the following substituted:

**102-9.15 Temporary Traffic Detection and Maintenance:** Provide temporary traffic detection and maintenance at existing, temporary, and new signalized intersections. Provide temporary traffic detection equipment listed on the APL. Restore any loss of detection within 12 hours. If permanent traffic detection cannot be restored within 12 hours, provide temporary detection. Ensure 90% accuracy per signal phase, measured at the initial installation and after any lane shifts, by comparing sample data collected from the detection system with ground truth data collected by human observation. Collect the sample and ground truth data for a minimum of five minutes during a peak and five minutes during an off-peak period with a minimum three detections for each signal phase. Perform the test in the presence of the Engineer.