## LOWERING DEVICE INSTALLATION NOTES:

- Place the lowering cable that moves within the pole in an 1. interior conduit to prevent it from tangling or interfering with any electrical wire that is in the pole. Ensure that any eléctrical wire within the pole is routed securely and free from slack.
- Mount lowering arm perpendicular to the roadway or as shown in the plans. Position CCTV pole so that the camera can be 2. safely lowered without requiring lane closures.
- Coordinate all lowering device hardware requirements 3. (including Tenon, Tenon mounting plates, parking stand, etc.) with lowering device manufacturer.

## POLE NOTES:

- 1. Pole Material Specifications:
  - a. Pole: Use Class VI Concrete with 6 ksi minimum strength at transfer.
  - b. Prestressing Strands: ASTM A416 Grade 270 low relaxation.
  - c. Reinforcing Steel: ASTM A615 Grade 60.
  - d. Spiral Reinforcing: ASTM A1064 Cold-Drawn.
  - e. Bolts: ASTM F1554, Grade 55. Nuts: ASTM A563, Grade A Heavy Hex. Washers: ASTM F436.
  - f. Steel plates and Pole Cap: ASTM A36 or ASTM A709 Grade 50.
  - g. Galvanization: Bolts, nuts and washers: ASTM F2329 All other steel: ASTM A123
- The pole shall be round or 12-sided. 2.
- З. Cut the tip end of the prestressed strand first or simultaneously with the butt end.
- 4. For spiral reinforcing, one turn is required for spiral splices and two turns are required at the top and bottom of poles.
- 5. For Reinforcing Steel, lap splice to consist of a 3'-0" lap length at each splice. No more than two opposing rebar to be spliced at the same cross section. Stagger lap splices as needed.

- 6. Section 400
- 7. Provide a 1" minimum cover.
- 8 plated screws.
- 9. Financial Project ID Pole Manufacturer Pole Length
- 10. Install pole plumb.
- detailed in the plans.

1111	TION.		



2016 DESIGN STANDARDS

CONCRETE CCTV POLE

Provided a Class 3 surface finish in accordance with Specification

Provide handhole and coupler cover plates made of non-corrosive materials. Attach cover plates to poles using lead anchors or threaded inserts embedded in the poles in conjunction with round headed chrome

Provide Identification Markings on the poles where indicated on the following sheets. Include the following information using inset numerals with 1" height or as approved in the Producers' Quality Control Program:

11. Tie ground wires to the interior of reinforcing steel as necessary to prevent displacement during concreting operations.

12. This Design Standard is considered fully detailed and no shop drawings are necessary. Submit Shop Drawings for minor modification's not

13. Storage, Handling and Erection locations shown may vary within ± 3".

## GENERAL NOTES

INDEX NO.	SHEET NO.
18113	1 of 4

Conduit Entry Hole

0

Min. Wall

Thickness

Tip

(in)

3

3

3

3

3

3

3

3

3

3

D

1" Lifting Hole

2" Couplings

Total

Taper\*\*

(in/ft)

0.18

0.18

0.18

0.18

0.18

Total

(in/ft)

0.216

0.18

0.216

0.18

0.216

0.18

0.216

0.18

0.216

0.18

Void

Taper

(in/ft)

0.192

0.172

0.192

0.173

0.192

0.173

0.192

0.174

0.192

0.174

ROUND POLE DESIGN TABLE

Α

Mold Seam

С



CONCRETE CCTV POLE



Conduit Entry Hole

Ground Lug Handhole Box Pole Identification Markings

## POLE CONFIGURATION TOP VIEW

12-SIDED POLE DESIGN TABLE*						
Void Taper (in/ft)	Min. Wall Thickness Tip (in)	Min. Wall Thickness Butt End (in)	Tip Diameter (in)	Butt Diameter (in)	Strand Pattern	Strand Diameter***
0.18	3	3	12	23.34	1	0.6"
0.18	3	3	12	24.42	1	0.6"
0.18	3	3	12	25.5	2	0.6"
0.18	3	3	12	26.4	2	0.6"
0.18	3	3	12	27.48	2	0.6"

ABLE				
Min. Wall Thickness Butt End (in)	Tip Diameter (in)	Butt Diameter (in)	Strand Pattern	Strand Diameter***
3.76	12.15	25.76	3	0.5"
3.5	12.0	23.34	4	0.5"
3.83	12.15	27.05	3	0.5"
3.5	12.0	24.42	4	0.5"
3.9	12.15	28.35	3	0.5"
3.5	12.0	25.5	4	0.5"
3.96	12.15	29.43	3	0.5"
3.5	12.0	26.4	4	0.5"
4.03	12.15	30.73	3	0.5"
3.5	13.0	28.48	4	0.5"

POLE DE	POLE DESIGN TABLES			
	INDEX NO.	SHEET NO.		
	18113	2 of 4		





DETAIL		
' x 1½" SCH. 40 Pipe		
<del>m</del>		
ION		
TAIL		
	MDEX	CUEFT
	NO.	NO.

4 of 4